

PAM250 Series Power Supply

Standard Models
PAS250-X-Y₁ ... Y_n

Tailored Models
PAS250-60ZZZ

Custom Models
PAS250-61ZZZ

	Voltage and Current Ratings		Standard Options
X Codes	Volts	Amps	Y Code Descriptions
1	Not Available		A 12Vdc, 0.5A Auxiliary Output** B Droop Share*
2	Not Available		C Fan Assembly** E DCOK Invert F PF Invert
3	Not Available		G Field configurable options – B, I, and J I Single Wire Share*
4	12.0	21.0	J Square Current Limit K Molex Connector, 7A max. (#8 stud standard)
5	15.0	17.0	M Metric Mounting O ORing Diode
6	24.0	10.5	R Remote On/Off (closed is OFF) S Remote On/Off Invert (open is OFF)
7	28.0	9.0	*Includes Option J **Options A and C are not available together
8	36.0	7.2	
9	48.0	5.5	
			Tailored Units (no safety changes)
			60ZZZ, where ZZZ = Factory Assigned Number Harnesses Added, Special test data, Etc.
			Custom Units (safety critical changes)
			61ZZZ, where ZZZ = Factory Assigned Number